

MRFBPF-922-6-Q6

Cavity Filter

Electrical Properties:

NO	Items	Specifications
1	Frequency Range	919MHz~925MHz
2	Insertion Loss at Center Frequency	≤2.0dB
3	Pass Band Ripple	≤1.0dB
4	VSWR	≤1.5
5	Attenuation	≥60dB@909MHz\935MHz
6	Impedance	50 Ohms
7	Power	≥2 Watts (CW)
8	Port Connectors	SMA-Female
9	Surface Finish	Silver Plating
10	Configuration	As Below

Drawing (unit mm):

